



Message Implementation Guideline

DESADV

based on

DESADV

Despatch Advice Message

EDIFACT D.97A

Version: D.97A
Variant: 2013
Issue date: 01.11.2020
Author: ITE
Contact: EDI@seg-automotive.com

EDIFACT DESADV D.97A

Despatch Advice Message



Structure / Table of Contents

Counter	No	Tag	St	MaxOcc	Level	Content
0000	1	UNA	C	1	0	Service string advice
0000	2	UNB	M	1	0	Interchange header
0010	3	UNH	M	1	0	Message header
0020	4	BGM	M	1	0	Beginning of message
0030	5	DTM	M	1	1	Date delivery note
0030	6	DTM	C	1	1	Despatch date
0050	7	MEA	M	1	1	Gross weight
0050	8	MEA	C	1	1	Net Weight
0050	9	MEA	C	1	1	Number of packs
0060	10	MOA	C	1	1	Total invoice amount
0070		SG1	C	1	1	Invoice references
0080	11	RFF	M	1	1	Invoice number
0070		SG1	M	1	1	Loading references
0080	12	RFF	M	1	1	Loading reference number
0090	13	DTM	C	1	2	Shipment reference date
0100		SG2	M	1	1	Buyer
0110	14	NAD	M	1	1	SEG receiving plant
0100		SG2	M	1	1	Seller/Supplier
0110	15	NAD	M	1	1	Supplier number assigned by SEG
0100		SG2	M	1	1	Delivery party
0110	16	NAD	M	1	1	Unloading point
0120	17	LOC	C	1	2	Warehouse
0190		SG5	C	1	1	Terms of delivery
0200	18	TOD	M	1	1	Terms of delivery and transport
0230		SG6	M	1	1	Means of transport
0240	19	TDT	M	1	1	Details of transport
0260		SG7	M	1	2	Ship-to information
0270	20	LOC	M	1	2	Ship-to location
0280	21	DTM	M	1	3	Supply date
0260		SG7	C	1	2	Departure information
0270	22	LOC	M	1	2	Place of departure
0280	23	DTM	C	1	3	Despatch date
0370		SG10	M	9999	1	Despatch control line
0380	24	CPS	M	1	1	Consignment packing sequence
0400		SG11	C	9999	2	Group of packaging items
0410	25	PAC	M	1	2	Packaging details
0430	26	QTY	C	1	3	Quantity per package
0470		SG13	C	1000	3	Individual packaging item

Counter = Counter of segment/group within the standard
 No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

Structure / Table of Contents

Counter	No	Tag	St	MaxOcc	Level	Content
0480	27	PCI	M	1	3	Package identification
0490	28	RFF	C	1	4	Customer process specification number
0510	29	GIR	C	1	4	Kanban card number
0510	30	GIR	C	98	4	Label numbers
0520		SG14	C	99	4	Goods identity number
0530	31	GIN	M	1	4	Label Number
0550		SG15	C	9999	2	Article and Despatched Article
0560	32	LIN	M	1	2	Line item
0570	33	PIA	C	1	3	Vendor's part number
0570	34	PIA	C	1	3	Charge
0570	35	PIA	C	1	3	Engineering change level
0580	36	IMD	C	1	3	Ship to stock
0590	37	MEA	C	1	3	Packs per position
0600	38	QTY	C	1	3	Despatch quantity
0600	39	QTY	M	1	3	Delivery quantity
0610	40	ALI	C	1	3	Country of origin
0650	41	DTM	C	1	3	Expiry date
0690	42	FTX	C	10	3	General information
0710		SG16	M	1	3	SEG Order reference
0720	43	RFF	M	1	3	SEG Order number
0710		SG16	C	1	3	Order confirmation reference
0720	44	RFF	M	1	3	Order confirmation number
0760		SG17	C	1	3	Dangerous goods information
0770	45	DGS	M	1	3	Dangerous goods
0880		SG20	C	9999	3	Package identification group
0890	46	PCI	M	1	3	Package identification
0910	47	MEA	C	1	4	First tariff measurements
0910	48	MEA	C	1	4	Second tariff measurements
0930		SG21	C	1	4	Charge number
0940	49	GIN	M	1	4	Goods identify number
1040	50	UNT	M	1	0	Message trailer
0000	51	UNZ	M	1	0	Interchange trailer

Counter = Counter of segment/group within the standard
 No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

EDIFACT DESADV D.97A

Despatch Advice Message



Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0000	1	UNA	C	1	0	Service string advice

		Standard	Implementation	
Tag	Name	St Format	St Format	Usage / Remark
UNA				
UNA1	Component data element separator	M an1	M an1	
UNA2	Data element separator	M an1	M an1	
UNA3	Decimal notation	M an1	M an1	
UNA4	Release indicator	M an1	M an1	
UNA5	Reserved for future use	M an1	M an1	
UNA6	Segment terminator	M an1	M an1	

Remark:

Example:

UNA:+. ? ' |

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

EDIFACT DESADV D.97A

Despatch Advice Message



Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0000	2	UNB	M	1	0	Interchange header

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
UNB				
S001	SYNTAX IDENTIFIER	M	M	
0001	Syntax identifier	M a4	M a4	UNOA UN/ECE level A 1 Version 1
0002	Syntax version number	M n1	M n1	
S002	INTERCHANGE SENDER	M	M	
0004	Sender identification	M an..35	M an..35	SEG supplier number
0007	Partner identification code qualifier	C an..4	C an..4	
0008	Address for reverse routing	C an..14	N	Not used
S003	INTERCHANGE RECIPIENT	M	M	
0010	Recipient identification	M an..35	M an..35	
0007	Partner identification code qualifier	C an..4	N	Not used
0014	Routing address	C an..14	R an..14	Code of ordering plant
S004	DATE/TIME OF PREPARATION	M	M	
0017	Date of preparation	M n6	M n6	
0019	Time of preparation	M n4	M n4	
0020	Interchange control reference	M an..14	M an..14	
S005	RECIPIENT'S REFERENCE PASSWORD	C	C	
0022	Recipient's reference/password	M an..14	M an..14	
0025	Recipient's reference/password qualifier	C an2	N	Not used
0026	Application reference	C an..14	N	Not used
0029	Processing priority code	C a1	N	Not used
0031	Acknowledgement request	C n1	N	Not used
0032	Communications agreement ID	C an..35	N	Not used
0035	Test indicator	C n1	C n1	in case of test 1 Interchange is a test

Remark:

Example:

UNB+UNOA:1+000123456:ZZZ+SEGAUTOMOTIVE::0780+040706:1531+174+DESADV+++++1'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

EDIFACT DESADV D.97A

Despatch Advice Message



Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0010	3	UNH	M	1	0	Message header

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
UNH				
0062	Message reference number	M an..14	M an..14	
S009	MESSAGE IDENTIFIER	M	M	
0065	Message type identifier	M an..6	M an..6	DESADV Despatch advice message
0052	Message type version number	M an..3	M an..3	D Draft version/UN/EDIFACT Directory
0054	Message type release number	M an..3	M an..3	97A Release 1997 - A
0051	Controlling agency	M an..2	M an..2	UN UN/ECE/TRADE/WP.4
0057	Association assigned code	C an..6	N	Not used
0068	Common access reference	C an..35	C an..35	
S010	STATUS OF THE TRANSFER	C	N	
0070	Sequence message transfer number	M n..2	N	Not used
0073	First/last sequence message transfer indication	C a1	N	Not used

Remark:

Example:

UNH+1+DESADV:D:97A:UN+EDDS05'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

EDIFACT DESADV D.97A

Despatch Advice Message



Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0020	4	BGM	M	1	0	Beginning of message

		Standard		Implementation		
Tag	Name	St	Format	St	Format	Usage / Remark
BGM						
C002	DOCUMENT/MESSAGE NAME	C		C		
1001	Document/message name, coded	C	an..3	C	an..3	351 Despatch advice
1131	Code list qualifier	C	an..3	N		Not used
3055	Code list responsible agency, coded	C	an..3	N		Not used
1000	Document/message name	C	an..35	N		Not used
C106	DOCUMENT/MESSAGE IDENTIFICATION	C		R		
1004	Document/message number	C	an..35	R	an..35	
1056	Version	C	an..9	N		Not used
1060	Revision number	C	an..6	N		Not used
1225	Message function, coded	C	an..3	C	an..3	9 Original
4343	Response type, coded	C	an..3	N		Not used

Remark:

Example:

BGM+351+6P258019+9'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional, O=Optional, F=Floating, D=Dependent, A=Advised, S=Situational, X=Not used, N=Not recommended)

EDIFACT DESADV D.97A

Despatch Advice Message



Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0030	5	DTM	M	1	1	Date delivery note

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
DTM				
C507	DATE/TIME/PERIOD	M	M	
2005	Date/time/period qualifier	M an..3	M an..3	137 Document/message date/time
2380	Date/time/period	C an..35	R an..35	
2379	Date/time/period format qualifier	C an..3	R an..3	102 CCYYMMDD 201 YYMMDDHHMM 203 CCYYMMDDHHMM

Remark:

Example:

DTM+137:20041018:102'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

EDIFACT DESADV D.97A

Despatch Advice Message



Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0030	6	DTM	C	1	1	Despatch date

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
DTM				
C507	DATE/TIME/PERIOD	M	M	
2005	Date/time/period qualifier	M an..3	M an..3	11 Despatch date and or time
2380	Date/time/period	C an..35	R an..35	
2379	Date/time/period format qualifier	C an..3	R an..3	102 CCYYMMDD 201 YYMMDDHHMM 203 CCYYMMDDHHMM

Remark:

Example:

DTM+11:20041018:102'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

EDIFACT DESADV D.97A

Despatch Advice Message



Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0050	7	MEA	M	1	1	Gross weight

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
MEA				
6311	Measurement purpose qualifier	M an..3	M an..3	WT Weights
C502	MEASUREMENT DETAILS	C	R	
6313	Property measured, coded	C an..3	R an..3	AAD Total gross weight
6321	Measurement significance, coded	C an..3	N	Not used
6155	Measurement attribute identification	C an..17	N	Not used
6154	Measurement attribute	C an..70	N	Not used
C174	VALUE/RANGE	C	R	
6411	Measure unit qualifier	M an..3	M an..3	Use UN/ECE Recommendation 20, for example KGM kilogram
6314	Measurement value	C an..18	R an..18	
6162	Range minimum	C n..18	N	Not used
6152	Range maximum	C n..18	N	Not used
6432	Significant digits	C n..2	N	Not used
7383	Surface/layer indicator, coded	C an..3	N	Not used

Remark:

Example:

MEA+WT+AAD+KGM:22825.00'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

EDIFACT DESADV D.97A

Despatch Advice Message



Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0050	8	MEA	C	1	1	Net Weight

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
MEA				
6311	Measurement purpose qualifier	M an..3	M an..3	WT Weights
C502	MEASUREMENT DETAILS	C	R	
6313	Property measured, coded	C an..3	R an..3	AAF Net net weight
6321	Measurement significance, coded	C an..3	N	Not used
6155	Measurement attribute identification	C an..17	N	Not used
6154	Measurement attribute	C an..70	N	Not used
C174	VALUE/RANGE	C	R	
6411	Measure unit qualifier	M an..3	M an..3	Use UN/ECE Recommendation 20, for example KGM kilogram
6314	Measurement value	C an..18	R an..18	
6162	Range minimum	C n..18	N	Not used
6152	Range maximum	C n..18	N	Not used
6432	Significant digits	C n..2	N	Not used
7383	Surface/layer indicator, coded	C an..3	N	Not used

Remark:

Example:

MEA+WT+AAF+KGM:21000.00'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

EDIFACT DESADV D.97A

Despatch Advice Message



Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0050	9	MEA	C	1	1	Number of packs

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
MEA				
6311	Measurement purpose qualifier	M an..3	M an..3	CT Counts
C502	MEASUREMENT DETAILS	C	C	
6313	Property measured, coded	C an..3	C an..3	SQ Shipped quantity
6321	Measurement significance, coded	C an..3	N	Not used
6155	Measurement attribute identification	C an..17	N	Not used
6154	Measurement attribute	C an..70	N	Not used
C174	VALUE/RANGE	C	C	
6411	Measure unit qualifier	M an..3	M an..3	Use UN/ECE Recommendation 20, for example NMP number of packs
6314	Measurement value	C an..18	C an..18	
6162	Range minimum	C n..18	N	Not used
6152	Range maximum	C n..18	N	Not used
6432	Significant digits	C n..2	N	Not used
7383	Surface/layer indicator, coded	C an..3	N	Not used

Remark:

Example:

MEA+CT+SQ+NMP : 5 '

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

EDIFACT DESADV D.97A

Despatch Advice Message



Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0060	10	MOA	C	1	1	Total invoice amount

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
MOA				
C516	MONETARY AMOUNT	M	M	
5025	Monetary amount type qualifier	M an..3	M an..3	39 Invoice total amount
5004	Monetary amount	C n..18	R n..18	
6345	Currency, coded	C an..3	R an..3	use ISO 4217 three alpha code, for example USD US Dollar
6343	Currency qualifier	C an..3	N	Not used
4405	Status, coded	C an..3	N	Not used

Remark:

Example:

MOA+39:5285.50:USD'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

EDIFACT DESADV D.97A

Despatch Advice Message



Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0070		SG1	C	1	1	Invoice references
0080	11	RFF	M	1	1	Invoice number

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
RFF				
C506	REFERENCE	M	M	
1153	Reference qualifier	M an..3	M an..3	IV Invoice number
1154	Reference number	C an..35	R an..35	
1156	Line number	C an..6	N	Not used
4000	Reference version number	C an..35	N	Not used

Remark:

Example:

RFF+IV:0000012345'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

EDIFACT DESADV D.97A

Despatch Advice Message



Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0070		SG1	M	1	1	Loading references
0080	12	RFF	M	1	1	Loading reference number

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
RFF				
C506	REFERENCE	M	M	
1153	Reference qualifier	M an..3	M an..3	SRN Shipment reference number
1154	Reference number	C an..35	R an..35	
1156	Line number	C an..6	N	Not used
4000	Reference version number	C an..35	N	Not used

Remark:

Example:

RFF+SRN:00004711'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

EDIFACT DESADV D.97A

Despatch Advice Message



Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0070		SG1	M	1	1	Loading references
0090	13	DTM	C	1	2	Shipment reference date

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
DTM				
C507	DATE/TIME/PERIOD	M	M	
2005	Date/time/period qualifier	M an..3	M an..3	171 Reference date/time
2380	Date/time/period	C an..35	R an..35	
2379	Date/time/period format qualifier	C an..3	R an..3	102 CCYYMMDD

Remark:

Example:

DTM+171:20041018:102'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

EDIFACT DESADV D.97A

Despatch Advice Message



Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0100		SG2	M	1	1	Buyer
0110	14	NAD	M	1	1	SEG receiving plant

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
NAD				
3035	Party qualifier	M an..3	M an..3	BY Buyer
C082	PARTY IDENTIFICATION DETAILS	C	R	
3039	Party id. identification	M an..35	M an..35	4-digit SEG plant code
1131	Code list qualifier	C an..3	N	Not used
3055	Code list responsible agency, coded	C an..3	R an..3	92 Assigned by buyer or buyer's agent
C058	NAME AND ADDRESS	C	N	
3124	Name and address line	M an..35	N	Not used
3124	Name and address line	C an..35	N	Not used
3124	Name and address line	C an..35	N	Not used
3124	Name and address line	C an..35	N	Not used
3124	Name and address line	C an..35	N	Not used
C080	PARTY NAME	C	N	
3036	Party name	M an..35	N	Not used
3036	Party name	C an..35	N	Not used
3036	Party name	C an..35	N	Not used
3036	Party name	C an..35	N	Not used
3036	Party name	C an..35	N	Not used
3045	Party name format, coded	C an..3	N	Not used
C059	STREET	C	N	
3042	Street and number/p.o. box	M an..35	N	Not used
3042	Street and number/p.o. box	C an..35	N	Not used
3042	Street and number/p.o. box	C an..35	N	Not used
3042	Street and number/p.o. box	C an..35	N	Not used
3164	City name	C an..35	N	Not used
3229	Country sub-entity identification	C an..9	N	Not used
3251	Postcode identification	C an..9	N	Not used
3207	Country, coded	C an..3	N	Not used

Remark:

Example:

NAD+BY+0780::92'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

EDIFACT DESADV D.97A



Despatch Advice Message

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0100		SG2	M	1	1	Seller/Supplier
0110	15	NAD	M	1	1	Supplier number assigned by SEG

		Standard	Implementation	
Tag	Name	St Format	St Format	Usage / Remark
NAD				
3035	Party qualifier	M an..3	M an..3	SE Seller SU Supplier
C082	PARTY IDENTIFICATION DETAILS	C	R	
3039	Party id. identification	M an..35	M an..35	
1131	Code list qualifier	C an..3	N	Not used
3055	Code list responsible agency, coded	C an..3	R an..3	92 Assigned by buyer or buyer's agent
C058	NAME AND ADDRESS	C	N	
3124	Name and address line	M an..35	N	Not used
3124	Name and address line	C an..35	N	Not used
3124	Name and address line	C an..35	N	Not used
3124	Name and address line	C an..35	N	Not used
3124	Name and address line	C an..35	N	Not used
C080	PARTY NAME	C	N	
3036	Party name	M an..35	N	Not used
3036	Party name	C an..35	N	Not used
3036	Party name	C an..35	N	Not used
3036	Party name	C an..35	N	Not used
3036	Party name	C an..35	N	Not used
3045	Party name format, coded	C an..3	N	Not used
C059	STREET	C	N	
3042	Street and number/p.o. box	M an..35	N	Not used
3042	Street and number/p.o. box	C an..35	N	Not used
3042	Street and number/p.o. box	C an..35	N	Not used
3042	Street and number/p.o. box	C an..35	N	Not used
3164	City name	C an..35	N	Not used
3229	Country sub-entity identification	C an..9	N	Not used
3251	Postcode identification	C an..9	N	Not used
3207	Country, coded	C an..3	N	Not used

Remark:

Example:

NAD+SU+000123456: :92'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

EDIFACT DESADV D.97A

Despatch Advice Message



Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0100		SG2	M	1	1	Delivery party
0110	16	NAD	M	1	1	Unloading point

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
NAD				
3035	Party qualifier	M an..3	M an..3	DP Delivery party
C082	PARTY IDENTIFICATION DETAILS	C	R	
3039	Party id. identification	M an..35	M an..35	
1131	Code list qualifier	C an..3	N	Not used
3055	Code list responsible agency, coded	C an..3	R an..3	92 Assigned by buyer or buyer's agent
C058 NAME AND ADDRESS				
3124	Name and address line	M an..35	N	Not used
3124	Name and address line	C an..35	N	Not used
3124	Name and address line	C an..35	N	Not used
3124	Name and address line	C an..35	N	Not used
3124	Name and address line	C an..35	N	Not used
C080 PARTY NAME				
3036	Party name	M an..35	N	Not used
3036	Party name	C an..35	N	Not used
3036	Party name	C an..35	N	Not used
3036	Party name	C an..35	N	Not used
3036	Party name	C an..35	N	Not used
3045	Party name format, coded	C an..3	N	Not used
C059 STREET				
3042	Street and number/p.o. box	M an..35	N	Not used
3042	Street and number/p.o. box	C an..35	N	Not used
3042	Street and number/p.o. box	C an..35	N	Not used
3042	Street and number/p.o. box	C an..35	N	Not used
3164	City name	C an..35	N	Not used
3229	Country sub-entity identification	C an..9	N	Not used
3251	Postcode identification	C an..9	N	Not used
3207	Country, coded	C an..3	N	Not used

Remark:

Example:

NAD+DP+REA08:::92'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

EDIFACT DESADV D.97A

Despatch Advice Message



Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0100		SG2	M	1	1	Delivery party
0120	17	LOC	C	1	2	Warehouse

		Standard	Implementation	
Tag	Name	St Format	St Format	Usage / Remark
LOC				
3227	Place/location qualifier	M an..3	M an..3	18 Warehouse
C517	LOCATION IDENTIFICATION	C	R	
3225	Place/location identification	C an..25	R an..25	
1131	Code list qualifier	C an..3	N	Not used
3055	Code list responsible agency, coded	C an..3	N	Not used
3224	Place/location	C an..70	N	Not used
C519	RELATED LOCATION ONE IDENTIFICATION	C	N	
3223	Related place/location one identification	C an..25	N	Not used
1131	Code list qualifier	C an..3	N	Not used
3055	Code list responsible agency, coded	C an..3	N	Not used
3222	Related place/location one	C an..70	N	Not used
C553	RELATED LOCATION TWO IDENTIFICATION	C	N	
3233	Related place/location two identification	C an..25	N	Not used
1131	Code list qualifier	C an..3	N	Not used
3055	Code list responsible agency, coded	C an..3	N	Not used
3232	Related place/location two	C an..70	N	Not used
5479	Relation, coded	C an..3	N	Not used

Remark:

Example:

LOC+18+BAU 500'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional, O=Optional, F=Floating, D=Dependent, A=Advised, S=Situational, X=Not used, N=Not recommended)

EDIFACT DESADV D.97A

Despatch Advice Message



Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0190		SG5	C	1	1	Terms of delivery
0200	18	TOD	M	1	1	Terms of delivery and transport

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
TOD				
4055	Terms of delivery or transport function, coded	C an..3	C an..3	6 Delivery condition
4215	Transport charges method of payment, coded	C an..3	N	Not used
C100	TERMS OF DELIVERY OR TRANSPORT	C	C	
4053	Terms of delivery or transport, coded	C an..3	R an..3	for example EXW Ex works CFR Cost & Freight CIF Cost, Insurance, Freight to named destination CIP Freight, Carriage, Insurance to destination CPT Freight, Carriage paid to destination DAF Delivery at frontier - Named place DDP Delivered duty paid to destination DDU Delivered duty unpaid to destination DEQ Delivered Ex Quay - Duty paid, Named port DES Delivered Ex ship - Named port of destination FAS Free alongside ship FCA Free carrier - Named point FOA FOB Airport - Named airport of departure FOB Free on Board - Named port of shipment FOR Free on Rail - Named departure point
1131	Code list qualifier	C an..3	N	Not used
3055	Code list responsible agency, coded	C an..3	N	Not used
4052	Terms of delivery or transport	C an..70	C an..70	
4052	Terms of delivery or transport	C an..70	N	Not used

Remark:

Example:

TOD+6++EXW:::EX WORKS'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional, O=Optional, F=Floating, D=Dependent, A=Advised, S=Situational, X=Not used, N=Not recommended)

EDIFACT DESADV D.97A

Despatch Advice Message



Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0230		SG6	M	1	1	Means of transport
0240	19	TDT	M	1	1	Details of transport

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
TDT				
8051	Transport stage qualifier	M an..3	M an..3	1 Inland transport
8028	Conveyance reference number	C an..17	C an..17	
C220	MODE OF TRANSPORT	C	C	
8067	Mode of transport, coded	C an..3	C an..3	1 Maritime transport 2 Rail transport 3 Road transport 4 Air transport
8066	Mode of transport	C an..17	C an..17	
C228	TRANSPORT MEANS	C	C	
8179	Type of means of transport identification	C an..8	C an..8	6 Aircraft 11 Ship 31 Truck
8178	Type of means of transport	C an..17	C an..17	
C040	CARRIER	C	C	
3127	Carrier identification	C an..17	N	Not used
1131	Code list qualifier	C an..3	N	Not used
3055	Code list responsible agency, coded	C an..3	N	Not used
3128	Carrier name	C an..35	C an..35	
8101	Transit direction, coded	C an..3	N	Not used
C401	EXCESS TRANSPORTATION INFORMATION	C	N	
8457	Excess transportation reason, coded	M an..3	N	Not used
8459	Excess transportation responsibility, coded	M an..3	N	Not used
7130	Customer authorization number	C an..17	N	Not used
C222	TRANSPORT IDENTIFICATION	C	N	
8213	Id. of means of transport identification	C an..9	N	Not used
1131	Code list qualifier	C an..3	N	Not used
3055	Code list responsible agency, coded	C an..3	N	Not used
8212	Id. of the means of transport	C an..35	N	Not used
8453	Nationality of means of transport, coded	C an..3	N	Not used
8281	Transport ownership, coded	C an..3	N	Not used

Remark:

Example:

TDT+1+123456789+3:EX WORKS+31:TRUCK+:::SPEDITEUR'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

EDIFACT DESADV D.97A

Despatch Advice Message



Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0260		SG7	M	1	2	Ship-to information
0270	20	LOC	M	1	2	Ship-to location

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
LOC				
3227	Place/location qualifier	M an..3	M an..3	7 Place of delivery
C517	LOCATION IDENTIFICATION	C	N	
3225	Place/location identification	C an..25	N	Not used
1131	Code list qualifier	C an..3	N	Not used
3055	Code list responsible agency, coded	C an..3	N	Not used
3224	Place/location	C an..70	N	Not used
C519	RELATED LOCATION ONE IDENTIFICATION	C	N	
3223	Related place/location one identification	C an..25	N	Not used
1131	Code list qualifier	C an..3	N	Not used
3055	Code list responsible agency, coded	C an..3	N	Not used
3222	Related place/location one	C an..70	N	Not used
C553	RELATED LOCATION TWO IDENTIFICATION	C	N	
3233	Related place/location two identification	C an..25	N	Not used
1131	Code list qualifier	C an..3	N	Not used
3055	Code list responsible agency, coded	C an..3	N	Not used
3232	Related place/location two	C an..70	N	Not used
5479	Relation, coded	C an..3	N	Not used

Remark:

Example:

LOC+7'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional, O=Optional, F=Floating, D=Dependent, A=Advised, S=Situational, X=Not used, N=Not recommended)

EDIFACT DESADV D.97A

Despatch Advice Message



Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0260		SG7	M	1	2	Ship-to information
0280	21	DTM	M	1	3	Supply date

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
DTM				
C507	DATE/TIME/PERIOD	M	M	
2005	Date/time/period qualifier	M an..3	M an..3	76 Delivery date/time, scheduled for
2380	Date/time/period	C an..35	R an..35	
2379	Date/time/period format qualifier	C an..3	R an..3	102 CCYYMMDD 203 CCYYMMDDHHMM

Remark:

Example:

DTM+76:200410191200:203'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

EDIFACT DESADV D.97A

Despatch Advice Message



Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0260		SG7	C	1	2	Departure information
0270	22	LOC	M	1	2	Place of departure

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
LOC				
3227	Place/location qualifier	M an..3	M an..3	5 Place of departure
C517	LOCATION IDENTIFICATION	C	C	
3225	Place/location identification	C an..25	C an..25	
1131	Code list qualifier	C an..3	N	Not used
3055	Code list responsible agency, coded	C an..3	N	Not used
3224	Place/location	C an..70	N	Not used
C519	RELATED LOCATION ONE IDENTIFICATION	C	N	
3223	Related place/location one identification	C an..25	N	Not used
1131	Code list qualifier	C an..3	N	Not used
3055	Code list responsible agency, coded	C an..3	N	Not used
3222	Related place/location one	C an..70	N	Not used
C553	RELATED LOCATION TWO IDENTIFICATION	C	N	
3233	Related place/location two identification	C an..25	N	Not used
1131	Code list qualifier	C an..3	N	Not used
3055	Code list responsible agency, coded	C an..3	N	Not used
3232	Related place/location two	C an..70	N	Not used
5479	Relation, coded	C an..3	N	Not used

Remark:

Example:

LOC+5+ABGANGSORT'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional, O=Optional, F=Floating, D=Dependent, A=Advised, S=Situational, X=Not used, N=Not recommended)

EDIFACT DESADV D.97A

Despatch Advice Message



Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0260		SG7	C	1	2	Departure information
0280	23	DTM	C	1	3	Despatch date

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
DTM				
C507	DATE/TIME/PERIOD	M	M	
2005	Date/time/period qualifier	M an..3	M an..3	11 Despatch date and or time
2380	Date/time/period	C an..35	R an..35	
2379	Date/time/period format qualifier	C an..3	R an..3	102 CCYYMMDD 203 CCYYMMDDHHMM

Remark:

Example:

DTM+11:199311161200:203'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

EDIFACT DESADV D.97A

Despatch Advice Message



Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0370		SG10	M	9999	1	Despatch control line
0380	24	CPS	M	1	1	Consignment packing sequence

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
CPS				
7164	Hierarchical id. number	M an..12	M an..12	
7166	Hierarchical parent id.	C an..12	N	Not used
7075	Packaging level, coded	C an..3	N	Not used

Remark:

Example:

CPS+1'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

EDIFACT DESADV D.97A

Despatch Advice Message



Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0400		SG11	C	9999	2	Group of packaging items
0410	25	PAC	M	1	2	Packaging details

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
PAC				
7224	Number of packages	C n..8	C n..8	
C531	PACKAGING DETAILS	C	C	
7075	Packaging level, coded	C an..3	C an..3	1 Inner 2 Intermediate 3 Outer 4 No packaging hierarchy
7233	Packaging related information, coded	C an..3	N	Not used
7073	Packaging terms and conditions, coded	C an..3	N	Not used
C202	PACKAGE TYPE	C	C	
7065	Type of packages identification	C an..17	C an..17	BX Box CB Beer crate CG Cage CT Carton DR Drum PC Parcel PA Packet PK Package
1131	Code list qualifier	C an..3	N	Not used
3055	Code list responsible agency, coded	C an..3	N	Not used
7064	Type of packages	C an..35	N	Not used
C402	PACKAGE TYPE IDENTIFICATION	C	C	
7077	Item description type, coded	M an..3	M an..3	X Semi-structured (code + text)
7064	Type of packages	M an..35	M an..35	
7143	Item number type, coded	C an..3	C an..3	BP Buyer's part number
7064	Type of packages	C an..35	C an..35	
7143	Item number type, coded	C an..3	C an..3	SA Supplier's article number
C532	RETURNABLE PACKAGE DETAILS	C	N	
8395	Returnable package freight payment responsibility, coded	C an..3	N	Not used
8393	Returnable package load contents, coded	C an..3	N	Not used

Remark:

Example:

PAC+2+3+PA+X:PACKMITTELNUMMER KUNDE:BP:PACKMITTELNUMMER LIEFERANT:SA '

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional, O=Optional, F=Floating, D=Dependent, A=Advised, S=Situational, X=Not used, N=Not recommended)

EDIFACT DESADV D.97A

Despatch Advice Message



Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0400		SG11	C	9999	2	Group of packaging items
0430	26	QTY	C	1	3	Quantity per package

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
QTY				
C186	QUANTITY DETAILS	M	M	
6063	Quantity qualifier	M an..3	M an..3	52 Quantity per pack
6060	Quantity	M n..15	M n..15	
6411	Measure unit qualifier	C an..3	N	Not used

Remark:

Example:

QTY+52:1000'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

EDIFACT DESADV D.97A

Despatch Advice Message



Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0470		SG13	C	1000	3	Individual packaging item
0480	27	PCI	M	1	3	Package identification

		Standard		Implementation	
Tag	Name	St	Format	St	Format / Usage / Remark
PCI					
4233	Marking instructions, coded	C	an..3	C	an..3 12 Mark running number of packages
C210	MARKS & LABELS	C		C	
7102	Shipping marks	M	an..35	M	an..35
7102	Shipping marks	C	an..35	C	an..35
7102	Shipping marks	C	an..35	N	Not used
7102	Shipping marks	C	an..35	N	Not used
7102	Shipping marks	C	an..35	N	Not used
7102	Shipping marks	C	an..35	N	Not used
7102	Shipping marks	C	an..35	N	Not used
7102	Shipping marks	C	an..35	N	Not used
7102	Shipping marks	C	an..35	N	Not used
7102	Shipping marks	C	an..35	N	Not used
8275	Container/package status, coded	C	an..3	N	Not used
C827	TYPE OF MARKING	C		N	
7511	Type of marking, coded	M	an..3	N	Not used
1131	Code list qualifier	C	an..3	N	Not used
3055	Code list responsible agency, coded	C	an..3	N	Not used

Remark:

Example:

PCI+12+25:54'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

EDIFACT DESADV D.97A

Despatch Advice Message



Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0470		SG13	C	1000	3	Individual packaging item
0490	28	RFF	C	1	4	Customer process specification number

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
RFF				
C506	REFERENCE	M	M	
1153	Reference qualifier	M an..3	M an..3	AEF Customer process specification number
1154	Reference number	C an..35	R an..35	
1156	Line number	C an..6	N	Not used
4000	Reference version number	C an..35	N	Not used

Remark:

Example:

RFF+AEF:GB45509-33'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

EDIFACT DESADV D.97A

Despatch Advice Message



Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0470		SG13	C	1000	3	Individual packaging item
0510	29	GIR	C	1	4	Kanban card number

		Standard	Implementation	
Tag	Name	St Format	St Format	Usage / Remark
GIR				
7297	Set identification qualifier	M an..3	M an..3	1 Product
C206	IDENTIFICATION NUMBER	M	M	
7402	Identity number	M an..35	M an..35	
7405	Identity number qualifier	C an..3	R an..3	AL Kanban card number
4405	Status, coded	C an..3	N	Not used
C206	IDENTIFICATION NUMBER	C	N	
7402	Identity number	M an..35	N	Not used
7405	Identity number qualifier	C an..3	N	Not used
4405	Status, coded	C an..3	N	Not used
C206	IDENTIFICATION NUMBER	C	N	
7402	Identity number	M an..35	N	Not used
7405	Identity number qualifier	C an..3	N	Not used
4405	Status, coded	C an..3	N	Not used
C206	IDENTIFICATION NUMBER	C	N	
7402	Identity number	M an..35	N	Not used
7405	Identity number qualifier	C an..3	N	Not used
4405	Status, coded	C an..3	N	Not used

Remark:

Example:

GIR+1+456123789:AL'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

EDIFACT DESADV D.97A

Despatch Advice Message



Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0470		SG13	C	1000	3	Individual packaging item
0510	30	GIR	C	98	4	Label numbers

		Standard	Implementation	
Tag	Name	St Format	St Format	Usage / Remark
GIR				
7297	Set identification qualifier	M an..3	M an..3	3 Package
C206	IDENTIFICATION NUMBER	M	M	
7402	Identity number	M an..35	M an..35	
7405	Identity number qualifier	C an..3	R an..3	ML Marking/label number
4405	Status, coded	C an..3	N	Not used
C206	IDENTIFICATION NUMBER	C	C	
7402	Identity number	M an..35	M an..35	
7405	Identity number qualifier	C an..3	R an..3	ML Marking/label number
4405	Status, coded	C an..3	N	Not used
C206	IDENTIFICATION NUMBER	C	N	
7402	Identity number	M an..35	N	Not used
7405	Identity number qualifier	C an..3	N	Not used
4405	Status, coded	C an..3	N	Not used
C206	IDENTIFICATION NUMBER	C	N	
7402	Identity number	M an..35	N	Not used
7405	Identity number qualifier	C an..3	N	Not used
4405	Status, coded	C an..3	N	Not used
C206	IDENTIFICATION NUMBER	C	N	
7402	Identity number	M an..35	N	Not used
7405	Identity number qualifier	C an..3	N	Not used
4405	Status, coded	C an..3	N	Not used

Remark:

Example:

GIR+3+000000001:ML+000000010:ML'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

EDIFACT DESADV D.97A

Despatch Advice Message



Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0520		SG14	C	99	4	Goods identity number
0530	31	GIN	M	1	4	Label Number

		Standard	Implementation	
Tag	Name	St Format	St Format	Usage / Remark
GIN				
7405	Identity number qualifier	M an..3	M an..3	ML Marking/label number
C208	IDENTITY NUMBER RANGE	M	M	
7402	Identity number	M an..35	M an..35	
7402	Identity number	C an..35	N	Not used
C208	IDENTITY NUMBER RANGE	C	C	
7402	Identity number	M an..35	M an..35	
7402	Identity number	C an..35	N	Not used
C208	IDENTITY NUMBER RANGE	C	N	
7402	Identity number	M an..35	N	Not used
7402	Identity number	C an..35	N	Not used
C208	IDENTITY NUMBER RANGE	C	N	
7402	Identity number	M an..35	N	Not used
7402	Identity number	C an..35	N	Not used
C208	IDENTITY NUMBER RANGE	C	N	
7402	Identity number	M an..35	N	Not used
7402	Identity number	C an..35	N	Not used

Remark:

Example:

GIN+ML+G+1234'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

EDIFACT DESADV D.97A

Despatch Advice Message



Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0550		SG15	C	9999	2	Article and Despatched Article
0560	32	LIN	M	1	2	Line item

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
LIN				
1082	Line item number	C an..6	C an..6	
1229	Action request/notification, coded	C an..3	N	Not used
C212	ITEM NUMBER IDENTIFICATION	C	R	
7140	Item number	C an..35	R an..35	
7143	Item number type, coded	C an..3	R an..3	BP Buyer's part number IN Buyer's item number
1131	Code list qualifier	C an..3	N	Not used
3055	Code list responsible agency, coded	C an..3	C an..3	92 Assigned by buyer or buyer's agent
C829	SUB-LINE INFORMATION	C	N	
5495	Sub-line indicator, coded	C an..3	N	Not used
1082	Line item number	C an..6	N	Not used
1222	Configuration level	C n..2	N	Not used
7083	Configuration, coded	C an..3	N	Not used

Remark:

Example:

LIN+1++1037356133:BP::92'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

EDIFACT DESADV D.97A



Despatch Advice Message

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0550		SG15	C	9999	2	Article and Despatched Article
0570	33	PIA	C	1	3	Vendor's part number

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
PIA				
4347	Product id. function qualifier	M an..3	M an..3	1 Additional identification
C212	ITEM NUMBER IDENTIFICATION	M	M	
7140	Item number	C an..35	R an..35	
7143	Item number type, coded	C an..3	R an..3	VP Vendor's (seller's) part number
1131	Code list qualifier	C an..3	N	Not used
3055	Code list responsible agency, coded	C an..3	C an..3	91 Assigned by seller or seller's agent
C212	ITEM NUMBER IDENTIFICATION	C	N	
7140	Item number	C an..35	N	Not used
7143	Item number type, coded	C an..3	N	Not used
1131	Code list qualifier	C an..3	N	Not used
3055	Code list responsible agency, coded	C an..3	N	Not used
C212	ITEM NUMBER IDENTIFICATION	C	N	
7140	Item number	C an..35	N	Not used
7143	Item number type, coded	C an..3	N	Not used
1131	Code list qualifier	C an..3	N	Not used
3055	Code list responsible agency, coded	C an..3	N	Not used
C212	ITEM NUMBER IDENTIFICATION	C	N	
7140	Item number	C an..35	N	Not used
7143	Item number type, coded	C an..3	N	Not used
1131	Code list qualifier	C an..3	N	Not used
3055	Code list responsible agency, coded	C an..3	N	Not used
C212	ITEM NUMBER IDENTIFICATION	C	N	
7140	Item number	C an..35	N	Not used
7143	Item number type, coded	C an..3	N	Not used
1131	Code list qualifier	C an..3	N	Not used
3055	Code list responsible agency, coded	C an..3	N	Not used

Remark:

Example:

PIA+1+Q6712D1357A701:VP::91'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

EDIFACT DESADV D.97A



Despatch Advice Message

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0550		SG15	C	9999	2	Article and Despatched Article
0570	34	PIA	C	1	3	Charge

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
PIA				
4347	Product id. function qualifier	M an..3	M an..3	1 Additional identification
C212	ITEM NUMBER IDENTIFICATION	M	M	
7140	Item number	C an..35	R an..35	
7143	Item number type, coded	C an..3	R an..3	AA Product version number
1131	Code list qualifier	C an..3	N	Not used
3055	Code list responsible agency, coded	C an..3	C an..3	91 Assigned by seller or seller's agent
C212	ITEM NUMBER IDENTIFICATION	C	N	
7140	Item number	C an..35	N	Not used
7143	Item number type, coded	C an..3	N	Not used
1131	Code list qualifier	C an..3	N	Not used
3055	Code list responsible agency, coded	C an..3	N	Not used
C212	ITEM NUMBER IDENTIFICATION	C	N	
7140	Item number	C an..35	N	Not used
7143	Item number type, coded	C an..3	N	Not used
1131	Code list qualifier	C an..3	N	Not used
3055	Code list responsible agency, coded	C an..3	N	Not used
C212	ITEM NUMBER IDENTIFICATION	C	N	
7140	Item number	C an..35	N	Not used
7143	Item number type, coded	C an..3	N	Not used
1131	Code list qualifier	C an..3	N	Not used
3055	Code list responsible agency, coded	C an..3	N	Not used
C212	ITEM NUMBER IDENTIFICATION	C	N	
7140	Item number	C an..35	N	Not used
7143	Item number type, coded	C an..3	N	Not used
1131	Code list qualifier	C an..3	N	Not used
3055	Code list responsible agency, coded	C an..3	N	Not used

Remark:

Example:

PIA+1+CHARGE:AA:::91'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

EDIFACT DESADV D.97A



Despatch Advice Message

Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0550		SG15	C	9999	2	Article and Despatched Article
0570	35	PIA	C	1	3	Engineering change level

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
PIA				
4347	Product id. function qualifier	M an..3	M an..3	1 Additional identification
C212	ITEM NUMBER IDENTIFICATION	M	M	
7140	Item number	C an..35	R an..35	
7143	Item number type, coded	C an..3	R an..3	EC Engineering change level
1131	Code list qualifier	C an..3	N	Not used
3055	Code list responsible agency, coded	C an..3	C an..3	91 Assigned by seller or seller's agent
C212	ITEM NUMBER IDENTIFICATION	C	N	
7140	Item number	C an..35	N	Not used
7143	Item number type, coded	C an..3	N	Not used
1131	Code list qualifier	C an..3	N	Not used
3055	Code list responsible agency, coded	C an..3	N	Not used
C212	ITEM NUMBER IDENTIFICATION	C	N	
7140	Item number	C an..35	N	Not used
7143	Item number type, coded	C an..3	N	Not used
1131	Code list qualifier	C an..3	N	Not used
3055	Code list responsible agency, coded	C an..3	N	Not used
C212	ITEM NUMBER IDENTIFICATION	C	N	
7140	Item number	C an..35	N	Not used
7143	Item number type, coded	C an..3	N	Not used
1131	Code list qualifier	C an..3	N	Not used
3055	Code list responsible agency, coded	C an..3	N	Not used
C212	ITEM NUMBER IDENTIFICATION	C	N	
7140	Item number	C an..35	N	Not used
7143	Item number type, coded	C an..3	N	Not used
1131	Code list qualifier	C an..3	N	Not used
3055	Code list responsible agency, coded	C an..3	N	Not used

Remark:

Example:

PIA+1+0815:EC::91'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

EDIFACT DESADV D.97A

Despatch Advice Message



Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0550		SG15	C	9999	2	Article and Despatched Article
0580	36	IMD	C	1	3	Ship to stock

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
IMD				
7077	Item description type, coded	C an..3	C an..3	F Free-form
7081	Item characteristic, coded	C an..3	C an..3	3 Ship to stock
C273	ITEM DESCRIPTION	C	N	
7009	Item description identification	C an..17	N	Not used
1131	Code list qualifier	C an..3	N	Not used
3055	Code list responsible agency, coded	C an..3	N	Not used
7008	Item description	C an..35	N	Not used
7008	Item description	C an..35	N	Not used
3453	Language, coded	C an..3	N	Not used
7383	Surface/layer indicator, coded	C an..3	N	Not used

Remark:

Example:

IMD+F+3 '

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

EDIFACT DESADV D.97A

Despatch Advice Message



Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0550		SG15	C	9999	2	Article and Despatched Article
0590	37	MEA	C	1	3	Packs per position

		Standard		Implementation		
Tag	Name	St	Format	St	Format	Usage / Remark
MEA						
6311	Measurement purpose qualifier	M	an..3	M	an..3	AAU Package
C502	MEASUREMENT DETAILS	C		N		
6313	Property measured, coded	C	an..3	N		Not used
6321	Measurement significance, coded	C	an..3	N		Not used
6155	Measurement attribute identification	C	an..17	N		Not used
6154	Measurement attribute	C	an..70	N		Not used
C174	VALUE/RANGE	C		R		
6411	Measure unit qualifier	M	an..3	M	an..3	NMP number of packs
6314	Measurement value	C	an..18	R	an..18	
6162	Range minimum	C	n..18	N		Not used
6152	Range maximum	C	n..18	N		Not used
6432	Significant digits	C	n..2	N		Not used
7383	Surface/layer indicator, coded	C	an..3	N		Not used

Remark:

Example:

MEA+AAU++NMP:2'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

EDIFACT DESADV D.97A

Despatch Advice Message



Segments

Counter	No	Tag	St	MaxOcc	Level	Name
	0550	SG15	C	9999	2	Article and Despatched Article
	0600	QTY	C	1	3	Despatch quantity

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
QTY				
C186	QUANTITY DETAILS	M	M	
6063	Quantity qualifier	M an..3	M an..3	12 Despatch quantity
6060	Quantity	M n..15	M n..15	
6411	Measure unit qualifier	C an..3	R an..3	Code specifying the unit of measurement, use UN/ECE Rec. 20, for example KGM kilogram PCE piece

Remark:

Example:

QTY+12:15:PCE'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

EDIFACT DESADV D.97A

Despatch Advice Message



Segments

Counter	No	Tag	St	MaxOcc	Level	Name
	0550	SG15	C	9999	2	Article and Despatched Article
	0600	QTY	M	1	3	Delivery quantity

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
QTY				
C186	QUANTITY DETAILS	M	M	
6063	Quantity qualifier	M an..3	M an..3	131 Delivery quantity
6060	Quantity	M n..15	M n..15	
6411	Measure unit qualifier	C an..3	R an..3	use ISO 4217 three alpha code, for example KGM kilogram PCE piece

Remark:

Example:

QTY+131:20:KGM'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

EDIFACT DESADV D.97A

Despatch Advice Message



Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0550		SG15	C	9999	2	Article and Despatched Article
0610	40	ALI	C	1	3	Country of origin

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
ALI				
3239	Country of origin, coded	C an..3	C an..3	Use ISO 3166-1, for example DE GERMANY
9213	Type of duty regime, coded	C an..3	C an..3	1 Origin subject to EC/EFTA preference
4183	Special conditions, coded	C an..3	N	Not used
4183	Special conditions, coded	C an..3	N	Not used
4183	Special conditions, coded	C an..3	N	Not used
4183	Special conditions, coded	C an..3	N	Not used
4183	Special conditions, coded	C an..3	N	Not used

Remark:

Example:

ALI+DE+1'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

EDIFACT DESADV D.97A

Despatch Advice Message



Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0550		SG15	C	9999	2	Article and Despatched Article
0650	41	DTM	C	1	3	Expiry date

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
DTM				
C507	DATE/TIME/PERIOD	M	M	
2005	Date/time/period qualifier	M an..3	M an..3	36 Expiry date
2380	Date/time/period	C an..35	R an..35	
2379	Date/time/period format qualifier	C an..3	R an..3	102 CCYYMMDD

Remark:

Example:

DTM+36:20080214:102'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

EDIFACT DESADV D.97A

Despatch Advice Message



Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0550		SG15	C	9999	2	Article and Despatched Article
0690	42	FTX	C	10	3	General information

		Standard	Implementation	
Tag	Name	St Format	St Format	Usage / Remark
FTX				
4451	Text subject qualifier	M an..3	M an..3	AAI General information
4453	Text function, coded	C an..3	C an..3	4 No action required
C107	TEXT REFERENCE	C	N	
4441	Free text identification	M an..17	N	Not used
1131	Code list qualifier	C an..3	N	Not used
3055	Code list responsible agency, coded	C an..3	N	Not used
C108	TEXT LITERAL	C	C	
4440	Free text	M an..70	M an..70	
4440	Free text	C an..70	C an..70	
4440	Free text	C an..70	C an..70	
4440	Free text	C an..70	N	Not used
4440	Free text	C an..70	N	Not used
3453	Language, coded	C an..3	N	Not used

Remark:

Example:

FTX+AAI+4+++text1:text2:text3'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

EDIFACT DESADV D.97A

Despatch Advice Message



Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0710		SG16	M	1	3	SEG Order reference
0720	43	RFF	M	1	3	SEG Order number

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
RFF				
C506	REFERENCE	M	M	
1153	Reference qualifier	M an..3	M an..3	ON Order number (purchase)
1154	Reference number	C an..35	R an..35	
1156	Line number	C an..6	C an..6	Required, if sent in DELFOR message
4000	Reference version number	C an..35	N	Not used

Remark:

Example:

RFF+ON:551032:001'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

EDIFACT DESADV D.97A

Despatch Advice Message



Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0710		SG16	C	1	3	Order confirmation reference
0720	44	RFF	M	1	3	Order confirmation number

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
RFF				
C506	REFERENCE	M	M	
1153	Reference qualifier	M an..3	M an..3	VN Order number (vendor)
1154	Reference number	C an..35	R an..35	
1156	Line number	C an..6	N	Not used
4000	Reference version number	C an..35	N	Not used

Remark:

Example:

RFF+VN:010203444'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

EDIFACT DESADV D.97A

Despatch Advice Message



Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0760		SG17	C	1	3	Dangerous goods information
0770	45	DGS	M	1	3	Dangerous goods

		Standard	Implementation	
Tag	Name	St Format	St Format	Usage / Remark
DGS				
8273	Dangerous goods regulations, coded	C an..3	C an..3	ADR European agreement on the international carriage of
C205	HAZARD CODE	C	C	
8351	Hazard code identification	M an..7	M an..7	
8078	Hazard substance/item/page number	C an..7	C an..7	
8092	Hazard code version number	C an..10	C an..10	
C234	UNDG INFORMATION	C	N	
7124	UNDG number	C n4	N	Not used
7088	Dangerous goods flashpoint	C an..8	N	Not used
C223	DANGEROUS GOODS SHIPMENT FLASHPOINT	C	N	
7106	Shipment flashpoint	C n3	N	Not used
6411	Measure unit qualifier	C an..3	N	Not used
8339	Packing group, coded	C an..3	N	Not used
8364	EMS number	C an..6	N	Not used
8410	MFAG	C an..4	N	Not used
8126	Trem card number	C an..10	N	Not used
C235	HAZARD IDENTIFICATION	C	N	
8158	Hazard identification number, upper part	C an..4	N	Not used
8186	Substance identification number, lower part	C an4	N	Not used
C236	DANGEROUS GOODS LABEL	C	N	
8246	Dangerous goods label marking	C an..4	N	Not used
8246	Dangerous goods label marking	C an..4	N	Not used
8246	Dangerous goods label marking	C an..4	N	Not used
8255	Packing instruction, coded	C an..3	N	Not used
8325	Category of means of transport, coded	C an..3	N	Not used
8211	Permission for transport, coded	C an..3	N	Not used

Remark:

Example:

DGS+ADR+3:3:B'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional, O=Optional, F=Floating, D=Dependent, A=Advised, S=Situational, X=Not used, N=Not recommended)

EDIFACT DESADV D.97A

Despatch Advice Message



Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0880		SG20	C	9999	3	Package identification group
0890	46	PCI	M	1	3	Package identification

		Standard		Implementation		
Tag	Name	St	Format	St	Format	Usage / Remark
PCI						
4233	Marking instructions, coded	C	an..3	C	an..3	21 Line item only
C210	MARKS & LABELS	C		C		
7102	Shipping marks	M	an..35	M	an..35	
7102	Shipping marks	C	an..35	N		Not used
7102	Shipping marks	C	an..35	N		Not used
7102	Shipping marks	C	an..35	N		Not used
7102	Shipping marks	C	an..35	N		Not used
7102	Shipping marks	C	an..35	N		Not used
7102	Shipping marks	C	an..35	N		Not used
7102	Shipping marks	C	an..35	N		Not used
7102	Shipping marks	C	an..35	N		Not used
7102	Shipping marks	C	an..35	N		Not used
8275	Container/package status, coded	C	an..3	N		Not used
C827	TYPE OF MARKING	C		N		
7511	Type of marking, coded	M	an..3	N		Not used
1131	Code list qualifier	C	an..3	N		Not used
3055	Code list responsible agency, coded	C	an..3	N		Not used

Remark:

Example:

PCI+21+33456789'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

EDIFACT DESADV D.97A

Despatch Advice Message



Segments

Counter	No	Tag	St	MaxOcc	Level	Name
	0880	SG20	C	9999	3	Package identification group
	0910	47 MEA	C	1	4	First tariff measurements

		Standard		Implementation		
Tag	Name	St	Format	St	Format	Usage / Remark
MEA						
6311	Measurement purpose qualifier	M	an..3	M	an..3	AAR 1st specified tariff quantity
C502	MEASUREMENT DETAILS	C		C		
6313	Property measured, coded	C	an..3	C	an..3	CT Contents of package
6321	Measurement significance, coded	C	an..3	C	an..3	4 Equal to
6155	Measurement attribute identification	C	an..17	C	an..17	34 Complete
6154	Measurement attribute	C	an..70	N		Not used
C174	VALUE/RANGE	C		C		
6411	Measure unit qualifier	M	an..3	M	an..3	use ISO 4217 three alpha code, for example GRM gram LTR litre
6314	Measurement value	C	an..18	C	an..18	
6162	Range minimum	C	n..18	N		Not used
6152	Range maximum	C	n..18	N		Not used
6432	Significant digits	C	n..2	N		Not used
7383	Surface/layer indicator, coded	C	an..3	N		Not used

Remark:

Example:

MEA+AAR+CT:4:34+GRM:1234567890.123'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

EDIFACT DESADV D.97A

Despatch Advice Message



Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0880		SG20	C	9999	3	Package identification group
0910	48	MEA	C	1	4	Second tariff measurements

		Standard		Implementation		
Tag	Name	St	Format	St	Format	Usage / Remark
MEA						
6311	Measurement purpose qualifier	M	an..3	M	an..3	AAS 2nd specified tariff quantity
C502	MEASUREMENT DETAILS	C		C		
6313	Property measured, coded	C	an..3	C	an..3	CT Contents of package
6321	Measurement significance, coded	C	an..3	C	an..3	4 Equal to
6155	Measurement attribute identification	C	an..17	C	an..17	34 Complete
6154	Measurement attribute	C	an..70	N		Not used
C174	VALUE/RANGE	C		C		
6411	Measure unit qualifier	M	an..3	M	an..3	GRM gram LTR litre
6314	Measurement value	C	an..18	C	an..18	
6162	Range minimum	C	n..18	N		Not used
6152	Range maximum	C	n..18	N		Not used
6432	Significant digits	C	n..2	N		Not used
7383	Surface/layer indicator, coded	C	an..3	N		Not used

Remark:

Example:

MEA+AAS+CT:4:34+LTR:1234567890.123'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

EDIFACT DESADV D.97A

Despatch Advice Message



Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0930		SG21	C	1	4	Charge number
0940	49	GIN	M	1	4	Goods identify number

		Standard	Implementation	
Tag	Name	St Format	St Format	Usage / Remark
GIN				
7405	Identity number qualifier	M an..3	M an..3	BX Batch number
C208	IDENTITY NUMBER RANGE	M	M	
7402	Identity number	M an..35	M an..35	
7402	Identity number	C an..35	N	Not used
C208	IDENTITY NUMBER RANGE	C	N	
7402	Identity number	M an..35	N	Not used
7402	Identity number	C an..35	N	Not used
C208	IDENTITY NUMBER RANGE	C	N	
7402	Identity number	M an..35	N	Not used
7402	Identity number	C an..35	N	Not used
C208	IDENTITY NUMBER RANGE	C	N	
7402	Identity number	M an..35	N	Not used
7402	Identity number	C an..35	N	Not used
C208	IDENTITY NUMBER RANGE	C	N	
7402	Identity number	M an..35	N	Not used
7402	Identity number	C an..35	N	Not used

Remark:

Example:

GIN+BX+CHARGE 0815'

No = Consecutive segment number
 MaxOcc = Maximum occurrence of the segment/group
 Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
 O=Optional, F=Floating, D=Dependent, A=Advised,
 S=Situational, X=Not used, N=Not recommended)

EDIFACT DESADV D.97A

Despatch Advice Message



Segments

Counter	No	Tag	St	MaxOcc	Level	Name
1040	50	UNT	M	1	0	Message trailer

		Standard	Implementation	
Tag	Name	St Format	St Format	Usage / Remark
UNT				
0074	Number of segments in a message	M n..6	M n..6	
0062	Message reference number	M an..14	M an..14	

Remark:

Example:

UNT+48+1'

No = Consecutive segment number
MaxOcc = Maximum occurrence of the segment/group
Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
O=Optional, F=Floating, D=Dependent, A=Advised,
S=Situational, X=Not used, N=Not recommended)

EDIFACT DESADV D.97A

Despatch Advice Message



Segments

Counter	No	Tag	St	MaxOcc	Level	Name
0000	51	UNZ	M	1	0	Interchange trailer

Standard			Implementation	
Tag	Name	St Format	St Format	Usage / Remark
UNZ				
0036	Interchange control count	M n..6	M n..6	
0020	Interchange control reference	M an..14	M an..14	

Remark:

Example:

UNZ+1+174'

No = Consecutive segment number
MaxOcc = Maximum occurrence of the segment/group
Counter = Counter of segment/group within the standard

St = Status (M=Mandatory, R=Required, C=Conditional,
O=Optional, F=Floating, D=Dependent, A=Advised,
S=Situational, X=Not used, N=Not recommended)

EDIFACT DESADV D.97A

Despatch Advice Message



Example message

No. Tag	Example
0000 UNA	UNA:+.?'
0000 UNB	UNB+UNOA:1+000123456:ZZZ+SEGAUTOMOTIVE::0780+040706:1531+174+DESADV+++++1'
0010 UNH	UNH+1+DESADV:D:97A:UN+EDDS05'
0020 BGM	BGM+351+6P258019+9'
0030 DTM	DTM+137:20041018:102'
0030 DTM	DTM+11:20041018:102'
0050 MEA	MEA+WT+AAD+KGM:22825.00'
0050 MEA	MEA+WT+AAF+KGM:21000.00'
0050 MEA	MEA+CT+SQ+NMP:5'
0060 MOA	MOA+39:5285.50:USD'
SG1	
0080 RFF	RFF+IV:0000012345'
SG1	
0080 RFF	RFF+SRN:00004711'
0090 DTM	DTM+171:20041018:102'
SG2	
0110 NAD	NAD+BY+0780::92'
SG2	
0110 NAD	NAD+SU+000123456::92'
SG2	
0110 NAD	NAD+DP+REA08::92'
0120 LOC	LOC+18+BAU 500'
SG5	
0200 TOD	TOD+6++EXW:::EX WORKS'
SG6	
0240 TDT	TDT+1+123456789+3:EX WORKS+31:TRUCK+:::SPEDITEUR'
SG7	
0270 LOC	LOC+7'
0280 DTM	DTM+76:200410191200:203'
SG7	
0270 LOC	LOC+5+ABGANGSORT'
0280 DTM	DTM+11:199311161200:203'
SG10	
0380 CPS	CPS+1'
SG11	

Example message

No. Tag	Example
0410 PAC	PAC+2+3+PA+X:PACKMITTELNUMMER KUNDE:BP:PACKMITTELNUMMER LIEFERANT:SA'
0430 QTY	QTY+52:1000'
SG13	
0480 PCI	PCI+12+25:54'
0490 RFF	RFF+AEF:GB45509-33'
0510 GIR	GIR+1+456123789:AL'
0510 GIR	GIR+3+000000001:ML+000000010:ML'
SG14	
0530 GIN	GIN+ML+G+1234'
SG15	
0560 LIN	LIN+1++1037356133:BP::92'
0570 PIA	PIA+1+Q6712D1357A701:VP::91'
0570 PIA	PIA+1+CHARGE:AA::91'
0570 PIA	PIA+1+0815:EC::91'
0580 IMD	IMD+F+3'
0590 MEA	MEA+AAU++NMP:2'
0600 QTY	QTY+12:15:PCE'
0600 QTY	QTY+131:20:KGM'
0610 ALI	ALI+DE+1'
0650 DTM	DTM+36:20080214:102'
0690 FTX	FTX+AAI+4+++text1:text2:text3'
SG16	
0720 RFF	RFF+ON:551032:001'
SG16	
0720 RFF	RFF+VN:010203444'
SG17	
0770 DGS	DGS+ADR+3:3:B'
SG20	
0890 PCI	PCI+21+33456789'
0910 MEA	MEA+AAR+CT:4:34+GRM:1234567890.123'
0910 MEA	MEA+AAS+CT:4:34+LTR:1234567890.123'
SG21	
0940 GIN	GIN+BX+CHARGE 0815'
1040 UNT	UNT+48+1'
0000 UNZ	UNZ+1+174'